

			
~ 50 Hz	VA (1)	VA (1)	U_n gG

			
~ 60 Hz	VA (1)	VA (1)	U_n gG

LC1 F115/F150				
LX1 FF024	550	45	24V	12A
LX1 FF042	"	"	42V	8A
LX1 FF048	"	"	48V	6A
LX1 FF110	"	"	110/115V	4A
LX1 FF127	"	"	127 V	4A
LX1 FF220	"	"	220/230V	2A
LX1 FF240	"	"	240V	2A
LX1 FF380	"	"	380/400V	1A
LX1 FF415	"	"	415/440V	1A
LX1 FF500	"	"	500V	1A
LX1 FF660	"	"	660V	1A

LC1 F115/F150				
LX1 FF040	660	55	48V	6A
LX1 FF092	"	"	110V	4A
LX1 FF095	"	"	115/120V	4A
LX1 FF162	"	"	200/208V	2A
LX1 FF184	"	"	220V	2A
LX1 FF187	"	"	230/240V	2A
LX1 FF340	"	"	415V	2A
LX1 FF360	"	"	440V	1A
LX1 FF380	"	"	460/480V	1A
LX1 FF550	"	"	660V	1A

LC1 F185/F225				
LX1 FG024	805	55	24V	16A
LX1 FG042	"	"	42V	8A
LX1 FG048	"	"	48V	8A
LX1 FG110	"	"	110/115V	4A
LX1 FG127	"	"	127 V	4A
LX1 FG220	"	"	220/230V	2A
LX1 FG240	"	"	240V	2A
LX1 FG380	"	"	380/400V	1A
LX1 FG415	"	"	415/440V	1A
LX1 FG500	"	"	500V	1A
LX1 FG660	"	"	660V	1A

LC1 F185/F225				
LX1 FG040	970	66	48V	10A
LX1 FG092	"	"	110V	6A
LX1 FG095	"	"	115/120V	6A
LX1 FG162	"	"	200/208V	4A
LX1 FG184	"	"	220V	4A
LX1 FG187	"	"	230/240V	4A
LX1 FG340	"	"	415V	2A
LX1 FG360	"	"	440V	2A
LX1 FG380	"	"	460/480V	2A
LX1 FG550	"	"	660V	1A

(1) $\theta = 20^\circ\text{C}$